

FG Wilson XD250P2 | International Powered Used Diesel Generator Set

Year: 2012 | Used Condition

Ref: FWP699

| General Information

Engine Brand	Perkins
Engine Model	1306C-E87TAG6
Alternator Brand	Leroy-Somer
Alternator Model	LL5014J

| AUXILIARY SYSTEMS

Control Module	Woodward easYgen AMF
Cooling Radiator	50 °C Ambient Rating
Circuit Breaker	ABB SACE Tmax
Coolant Heater	TBC
Starting Battery	Yes
Fuel Tank	Yes - Integrated 1,004 Litre Base Tank
Base Frame	Heavy Duty Skid / Base Frame

| GENERATOR SET - KEY PARAMETERS

GENSET MODEL	XD250P2
POWER PRP	250 kVA PRP / 200 kW
POWER ESP	275 kVA ESP / 220 kW
FREQUENCY / SPEED	50 Hz / 1500 RPM
OUTPUT VOLTAGE	3 Ph - 415 / 240 V
POWER FACTOR	0.8 pf lagging
ENCLOSURE TYPE	Silent (Sound Attenuated)

| GENERATOR SET - KEY PARAMETERS

Inlet Socket	1





| DIMENSIONS & WEIGHT

Canopied / Silent Type

4150 LENGTH (mm)	1395 WIDTH (mm)	2140 HEIGHT (mm)	4059 WEIGHT (kg)
---------------------	--------------------	---------------------	---------------------

Disclaimer: Data shown is taken from available generator, engine and alternator plates/photos and FG Wilson XD250P2 published technical literature where applicable. It is provided for general guidance only. FW Power Generators Ltd accepts no liability for errors, omissions, variations or discrepancies. Customers must verify all critical specifications and suitability prior to purchase.

Office: +44 (0)1829 863497 | Mobile or WhatsApp: +44 07424 980523 | Email: info@fwpower.co.uk